



# POWERSAVE™

Compact protection for power supply  
For Continuous Power Protection Availability



## PowerValue™ – The Beauty of Power Protection Simplicity

PowerValue™ represents an accurately balanced combination of unmatched reliability, excellent electrical performance, exceptionally compact size and outstanding cost-efficiency housed in an attractive enclosure.



Cabinet A:  
Up to 15kVA with 10 min.



Cabinet B:  
Up to 40kVA with 10 min.



Cabinet C:  
Up to 40kVA with 20 min.

## Medium-sized power protection range with outstanding price/performance capability

PowerValue™ is a third-generation transformer-less double-conversion (VFI) power protection technology designed to protect a wide area of critical applications including server rooms, networks, telecommunication systems, industrial processes and medical equipment.

PowerValue™ addresses applications where the higher cost of parallelable or scalable power protection solutions are not justified. Furthermore, as PowerValue™ provides increased protection security and efficiency it can be used instead of multiple separate, smaller units spread throughout a facility.

The uniqueness of the PowerValue™ design lies in its technical simplicity which is based on Newave's transformerless, double-conversion (VFI = Voltage Frequency Independent) technology with unmatched reliability.

PowerValue™ is available in a variety of models and input/output configurations:

- PowerValue™ (1phase input and 1phase output), 7.5, 10 and 12 kVA
- PowerValue™ (3phase input and 1phase output), 7.5, 10, 15 and 20 kVA
- PowerValue™ (3phase input and 3phase output), 7.5, 10, 15, 20, 30 and 40 kVA

## Features and benefits

Provides more power protection value at a more affordable price

PowerValue™ has been designed to provide an optimised price/performance ratio. A number of exceptional features have been carefully selected and built into the PowerValue™ without a substantial increase of material contents in order to optimize both performance and cost benefits.

Benefits	Features
Continuous Uptime	Highest reliability is provided through mature, on-line double conversion, transformerless technology. Built-in reliability with redundant power supply, reduced cable harness, improved cooling of critical components.
Space Saving	Smallest foot-print and weight: 15kVA (3/3) = 0.26m <sup>2</sup> , weight w/o batteries = 75kg 40kVA (3/3) = 0.37m <sup>2</sup> , weight w/o batteries = 204kg
Cost Saving	Outstanding power and back-up-time density.
High Power Availability	Wide input voltage window (up to 40% for loads less than 60%) and input frequency window (35–70 Hz) allows high power availability even in environments where input power supply is unstable and sub-standard. Battery usage is minimised.
Low Cost of Ownership	Thanks to Energy Saving Inverter Switching (ESIS) high double conversion efficiencies (up to 95%) are achieved.
Low Audible Noise	Variable load-dependent DC-fan-speed reduces the audible noise, so that the UPS can be operated in office environments.
Integration in Networks	PowerValue™ has advanced monitoring and communication capabilities to keep you in constant command of your critical power protection system.
Protects Your Environment	PowerValue™ protects not only critical applications but also our environment. It is a true environmentally friendly UPS with limited hardware components (saving natural resources).

# Interfaces

User friendly, easy to install and easy to commission

PowerValue™ is a user-friendly UPS which is easy to install and commission. In the following pictures the various interfaces of the UPS are illustrated:

Interfaces for cabinet A, B and C



**User friendly Control Panel is composed of:**

- a. Mimic Diagram
- b. LC-Display
- c. Keyboard



Front View  
Cabinet A



Rear View  
Cabinet A

- SNMP-Slot
- Dry Port
- Smart Port RS 232
- Cooling Fans
- Input/battery/bypass fuses  
Manual bypass and  
Output breaker
- Input/Output Terminals
- Rollers/Castors



Front View  
Cabinet B\*



Rear View  
Cabinet B\*

- SNMP-Slot
- Dry Port
- Smart Port RS 232
- Input/battery fuses
- Bypass fuses  
Manual bypass and  
Output breaker
- Input/Output Terminals
- Rollers/Castors
- Cooling Fans

\*The position of the interfaces on the larger cabinet C are equivalent to cabinet B.

# Technical specifications PowerValue™ 11 and 31

GENERAL DATA		1-phase input/output (11)			3-phase input/1-phase output (31)			
Output Rated Power	kVA	7.5	10	12	7.5	10	15	20
Output Power Factor		0.7						
Topology		Double conversion (on-line)						
Construction		Standalone						
Static and Maintenance Bypass		Standard						
Cable entry		Cabinet A from rear, cabinet B and C from front						
Audible Noise With 100%/50% load	dB(A)	50/48	50/48	50/48	50/48	50/48	53/49	53/49
Inbuilt Batteries		Yes						
<b>INPUT</b>								
Voltage	V	1 x 220/230/240+N			3 x 380/220+N, 3 x 400/230+N, 3 x 415/240+N			
Voltage Tolerance (Ref. to 3x400/230 V)		For loads <100% (-23%, +15%), <80% (-30%, +15%), <60% (-40%, +15%)						
Current Form THDi	%	THDi=7-9%			THDi <25% standard (THDi=12-14% optional)			
Frequency	Hz	35-70						
Power Factor (electrically regulated)		0.98			0.95 standard (0.98 optional)			
Current Distortion	%	sinewave						
Inrush Current		Soft start						
Cabling		Hardwired						
<b>OUTPUT</b>								
Voltage	V	1 x 220/230/240+N						
Voltage Tolerance (Ref. to 3x400/230 V)		1% (linear load), 4% (non-linear load)						
Voltage Distortion	%	<2% linear load, <4% non-linear load (IEC/EN62040-3)						
Frequency	Hz	50 or 60						
Frequency Tolerance	Hz	±0.1 (free-running), ±2 or ±4 (with mains, adjustable)						
Overloading capability	%	125% / 10 min., 150% / 60 s						
Crest Factor		3 : 1						
<b>EFFICIENCY</b>								
Load 100/75/50/25%	%	Up to 94.5/94.5/93/91, AC-AC on-line mode						
Eco-Mode at 100% Load	%	98						
<b>ENVIRONMENT</b>								
Storage Temperature	°C	-25...+70						
Operating Temperature	°C	0...+40						
Maximum Altitude	m	Up to 1000m without derating, max. 3000m						
<b>COMMUNICATIONS</b>								
Interfaces		LC-Display (PDM), 1x RS232 1 x RS232 (SMART PORTS), customer input interfaces (Remote shutdown, GENSET-ON), customer output interfaces (Dry Ports)						
Options		Additional COM-Cards						
<b>STANDARDS</b>								
Safety		IEC/EN 62040-1-1, IEC/EN 60950-1						
Electromagnetic Comp. (EMC)		IEC/EN 61000-6-4 (product standard IEC/EN 62040-2 limit A (C2 UPS)) IEC/EN 61000-6-2 (product standard IEC/EN 62040-2 Criterion A (C2 UPS)) IEC/EN 61000-4-2, IEC/EN 61000-4-3, IEC/EN 61000-4-4, IEC/EN 61000-4-5, IEC/EN 61000-4-6						
Performance		IEC/EN 62040-3						
Product Certification		CE, GOST by TÜV						
Enclosure		IP 20						
Manufacturing		ISO 9001:2008, ISO 14001:2004						
Country of origin		Italy						
<b>WEIGHT, DIMENSIONS</b>								
		Cabinet Type						
		A (7.5–15kVA)			B (7.5–20kVA)		C (7.5–20kVA)	
Weight	kg	75			154		204	
Dimensions (WxHxD)	mm	340x820x800			450x1250x860		550x1650x890	

# Technical specifications PowerValue™ 33




GENERAL DATA		3-phase input/3-phase output (33)					
Output Rated Power	kVA	7.5	10	15	20	30	40
Output Power Factor		0.8					
Topology		Double conversion (on-line)					
Construction		Standalone					
Static and Maintenance Bypass		Standard					
Cable entry		Cabinet A from rear, Cabinet B and C from front					
Audible Noise with 100% / 50% load	dB(A)	50/48	50/48	43/49	53/49	59/51	63/53
Inbuilt Batteries		Yes					
INPUT							
Voltage	V	3 x 380/220+N, 3 x 400/230+N, 3 x 415/240+N					
Voltage Tolerance (Ref. to 3x400/230 V)		For loads <100% (-23%, +15%), <80% (-30%, +15%), <60% (-40%, +15%)					
Current Form THDi	%	THDi < 25% Standard (THDi=12-14% optional)					
Frequency	Hz	35-70					
Power Factor (electrically regulated)		0.95 Standard (0.98 optional)					
Current Distortion	%	sinewave					
Inrush Current		Soft start					
Cabling		Hardwired					
OUTPUT							
Voltage	V	3 x 380/220+N, 3 x 400/230+N, 3 x 415/240+N					
Voltage Tolerance (Ref. to 3x400/230 V)		±1% (linear load), ±3 (non-linear load)					
Voltage Distortion	%	<2% linear load, <4% non-linear load (IEC/EN62040-3)					
Frequency	Hz	50 or 60					
Frequency Tolerance	Hz	±0.1 (free-running), ±2 or ±4 (with mains, adjustable)					
Overloading capability	%	125%/10 min., 150%/60 s					
Permissible Unbalanced Load	%	100% (all 3 phases regulated independently)					
Crest Factor		3 : 1					
EFFICIENCY							
Load 100/75/50/25%	%	Up to 95/95/93.5/92, AC-AC online mode					
Eco-Mode at 100% Load	%	98					
ENVIRONMENT							
Storage Temperature	°C	-25...+70					
Operating Temperature	°C	0...+40					
Maximum Altitude	m	Up to 1000m without derating, max. 3000m					
COMMUNICATIONS							
Interfaces		LC-Display (PDM), 1x RS232 1 x RS232 (SMART PORTS), customer input interfaces (Remote shutdown, GENSET-ON), customer output interfaces (Dry Ports)					
Options		Additional COM-Cards					
STANDARDS							
Safety		IEC/EN 62040-1-1, IEC/EN 60950-1					
Electromagnetic Comp. (EMC)		IEC/EN 61000-6-4 (product standard IEC/EN 62040-2 limit A (C2 UPS)) IEC/EN 61000-6-2 (product standard IEC/EN 62040-2 Criterion A (C2 UPS)) IEC/EN 61000-4-2, IEC/EN 61000-4-3, IEC/EN 61000-4-4, IEC/EN 61000-4-5, IEC/EN 61000-4-6					
Performance		IEC/EN 62040-3					
Product Certification		CE, GOST by TÜV					
Enclosure		IP 20					
Manufacturing		ISO 9001:2008, ISO 14001:2004					
Country of origin		Italy					
WEIGHT, DIMENSIONS		Cabinet Type					
		A (7.5-40kVA)	B (7.5-40kVA)			C (7.5-40kVA)	
Weight	kg	75	154			204	
Dimensions (WxHxD)	mm	340x820x800	450x1250x860			550x1650x890	

## Battery flexibility

Compact size with capability of supplying longer back-up times without extra battery cabinet

PowerValue™ is provided in three cabinet sizes in order to allow longer battery back-up times and therefore avoid the use of additional battery cabinets. All PowerValue™ are equipped with a 6 Amp ripple-free battery charger that protects batteries and delays their aging process. Optional temperature-dependent charging function is provided. The advanced Battery Monitoring and Management algorithm monitors the battery continuously and in the unlikely event of a battery fault an early warning will be triggered.

## Battery configurations

Cabinet type*	Maximum Battery Configuration	Maximum Back-up (min.) with 100% load		UPS Rating (kVA)
	2 x 27 x 9Ah	28 (PF=0.8) 20 (PF=0.8) 14 (PF=0.8) 12 (PF=0.8)	33 (PF=0.7) 23 (PF=0.7) 18 (PF=0.7) 14 (PF=0.7)	7.5 10 12 15
	3 x 48 x 9Ah	96 (PF=0.8) 66 (PF=0.8) 52 (PF=0.8) 40 (PF=0.8) 26 (PF=0.8)	110 (PF=0.7) 78 (PF=0.7) 62 (PF=0.7) 46 (PF=0.7) 30 (PF=0.7)	7.5 10 12 15 20
		16 (PF=0.8) 11 (PF=0.8)		30 40
	2 x 40 x 28Ah	130 (PF=0.8) 76 (PF=0.8) 60 (PF=0.8) 35 (PF=0.8) 28 (PF=0.8)		10 15 20 30 40
* Cabinet (WxHxD): A 340x820x800mm / B 450x1250x860mm / C 550x1650x890mm				

### Options

Monitoring and control data are shown on an easy-to-understand front panel display featuring pushbutton controls, LCD readout for event logs and diagnostics and a mimic diagram for system status.

Wavemon shutdown and management software is compatible with all common operation systems.

The power protection system can be remotely monitored via RS232, volt-free relays or via SNMP Adapter.





## Newave Group Companies

### Newave Energy Holding SA

Via Luserte Sud 9  
CH-6572 Quartino  
T +41 (0) 91 850 29 29  
F +41 (0) 91 840 12 54  
info@newaveenergy.com  
www.newaveenergy.com

## Head Office: Operations, Sales & Marketing

### Newave SA

Via Luserte Sud 9  
CH-6572 Quartino  
T +41 (0) 91 850 29 29  
F +41 (0) 91 840 12 54  
info@newaveenergy.com  
www.newaveenergy.com

## Subsidiaries

### Austria

Newave Österreich GmbH  
Laxenburgerstrasse 252  
A-1230 Wien  
T +43 (1) 710 96 70 0  
F +43 (1) 710 96 70 12  
info@newaveups.at  
www.newaveups.at

### Hong Kong & China

Newave Energy Hong Kong Ltd  
Room 2506, West Tower,  
Shun Tak Centre  
HK-168-200 Connaught Road Central  
T +31 642 215 512  
sales-china@newave.com.cn  
www.newave.com.cn

### Italy

NEWAVE Italia  
Via Vincenzo Ussani, 90  
I-00151 Roma  
T +39 (0) 687 451 674  
T +39 (0) 665 31 316  
F +39 (0) 665 31 306  
info@newaveenergy.it  
www.newaveups.it

### Switzerland

Newave Energy AG  
Industriestrasse 5  
CH-5432 Neuenhof  
T +41 (0) 56 416 01 01  
F +41 (0) 56 416 01 00  
info@newaveenergy.ch  
www.newaveenergy.ch

### Finland

Newave Finland OY  
Niittyläntie 2  
FI-00620 Helsinki  
T +358 (0) 10 421 9400  
info@newaveups.fi  
www.newaveups.fi

### with branch office in China:

Newave Energy (Jiangmen) Limited  
9/F Kawa House, 49 Jiangshe Road,  
Jiangmen, GuangDong, China  
Postal Code: 529000  
T +86 750 368 0239  
F +86 750 368 0229  
sales-china@newave.com.cn  
www.newave.com.cn

### Latin America

Newave South America LTDA  
Rua Clodomiro Amazonas No. 1422  
Suite 68  
BR-04537-002 - São Paulo  
T +55 (11) 3045 0809  
F +55 (11) 3045 0764  
info@newavesam.com  
www.newaveups.com

### with branch office in Biel:

Am Wald 36  
CH-2504 Biel  
T +41 (0) 32 366 60 30  
F +41 (0) 32 366 60 35  
info@newaveenergy.ch  
www.newaveenergy.ch

### Germany

Newave USV Systeme GmbH  
Summerside Ave. C 207  
Baden Airpark  
D-77836 Rheinmünster  
T +49 (0) 7229 1866 0  
F +49 (0) 7229 1866 33  
zentrale@newave-usv.de  
www.newave-usv.de

### India

Newave Energy India Pvt. Ltd.  
818/819 Corporate Avenue,  
Sonawala Road, Goregaon East,  
Mumbai 400 0063  
T +91 (22) 4266 5151  
F +91 (22) 4266 5141  
rajesh.shah@newaveenergy.in  
www.newaveups.com

### Spain

Newave España SA  
Arturo Soria 329 | D  
ES-28033 Madrid  
T +34 (91) 768 22 22  
F +34 (91) 383 21 50  
newave@newave.es  
www.newave.es

### The Netherlands

Newave UPS Systems BV  
Stephensonweg 9  
NL-4207 HA Gorinchem  
T +31 (0) 183 64 6474  
F +31 (0) 183 62 3540  
info@newaveups.nl  
www.newaveups.nl

## Newave Certifications & Recognitions

